

◀ clamp meter ▶

- More: 1. [DE-3501/3502/3503/3505 AC digital](#)
 2. [DE-3511/3512/3513/3515 AC/DC digital](#)
 3. [DE-380/381/382 analog](#)
 4. [DE-3100/DE-3102/DE-3100R/DE-3102R AC mini digital](#)
 5. [DE-3103/DE-3104/DE-3103R/DE-3104R AC mini digital](#)
 6. [DE-3110/DE-3112/DE-3110R/DE-3112R AC/DC mini digital I](#)
 7. [DE-3506/3507 AC digital](#)
 8. [DE-3516/3517 AC/DC digital](#)

AC/DC digital clamp meter

Model # [DE-3511](#) / [DE-3512](#) / [DE-3513](#) / [DE-3515](#) 

Features :

- Peak hold (ACA & DCA)
- Auto range & manual range
- True RMS (DE-3513 & DE-3515)
- One touch to zero set (DCA)
- Data hold
- Min. / Max hold (parallel record)
- Range hold
- Auto power off selection
- Synchronize measurement of Hz & ACA or ACV
- Temp. measurement (DE-3512 & DE-3515)
- High accuracy

Size : 241 (L) x 91 (W) x 45 (H) mm

Weight : 390g

Specifications:

- ACA (0.01A ~ 1000A)
 - DCA (0.01A ~ 1000A)
 - ACV (0.001V ~ 600V)
 - DCV (0.001V ~ 600V)
 - Ω (0.1 Ω ~ 40M Ω)
 - Frequency (0.1Hz ~ 4000Hz)
 - Continuity check
 - Temperature test / Resolution
 - Max clamp size
 - Over range indicator
 - Low battery indicator
 - LCD display
 - Sampling rate
 - Transient sampling rate
 - Applicable height
 - Applicable circuit voltage
- CE approval : IEC 61010-1, IEC 61010-2-032
 - : 40A / 400A / 1000A
 - : **40A / 400A / 1000A**
 - : 4V / 40V / 400V / 600V
 - : 4V / 40V / 400V / 600V
 - : 400 Ω / 4K Ω / 40K Ω / 400K Ω / 4M Ω / 40M Ω
 - : 400Hz / 4000Hz
 - : Yes
 - : -50 $^{\circ}$ C~1100 $^{\circ}$ C (-58 $^{\circ}$ F ~ 2010 $^{\circ}$ F) / 1 $^{\circ}$ C (2 $^{\circ}$ F)
 - : -50 $^{\circ}$ C~436.9 $^{\circ}$ C (-58 $^{\circ}$ F ~ 436.9 $^{\circ}$ F) / 0.1 $^{\circ}$ C (0.2 $^{\circ}$ F)
 - : \varnothing 40mm or 10x47mm
 - : OL & **Beep**
 - : Yes
 - : 3 3/4 digits 4300 counts
 - : approx. 2 times / sec.
 - : **approx. 9 times / sec.**
 - : up to 2000m (above sea level)
 - : AC 600V or less

 [Download](#)

[Cli](#) [P1](#), [P2](#), [P3](#), [P4](#), [P5](#), [P6](#) , [P7](#), [P8](#)

[analog multimeter](#) • [digital-multimeter](#) • [clamp meter](#) • [panel meter](#) • [Electrical shunt /Shunt resistor](#) • [C.T./Hall sensor](#)
[EMF tester](#) • [vu meter](#) • [thermometer](#) / [light](#) / [sound meter](#) • [other](#) • [showroom](#) • [inquiry form](#) • [home](#)